RSR04E_08E_16E

1. ..... **4**

1.1. 4
1.2. 5
1.3. TAB 8
1.4. show 8
1.5. set 10
1.6. commit rollback 11

2. RSR **14**

2.1. 14
2.2. SNMP 15
2.3. 17
2.4. VLAN 21
2.5. VRRP 21
2.6. 23
2.7. Policy 24
2.8. GRE Tunnel 27
2.9. NAT 28

3.

4.6.4. 39
4.6.5. 41
4.7. 41
4.7.1. 42
4.7.2. 42
4.7.3. 44
4.7.4. 48
4.7.5. 50
4.7.6. 54

1.

RSR CLI(command-line interface) web

console telnet
console telnet IP
telnet root

1.1.

CLI >,
configure edit

user@host> #

1.2.

RSR protocols
bgp isis ospf ospf
area traceoptions area interface area-range
dead-interval hello-interval

1.3.

```
    Logical interface fe-1/3/0.0 (Index 83) (SNMP ifIndex 71)
      Flags: SNMP-Traps 0x4000 VLAN-Tag [ 0x8100.33 ]    Encapsulation: ENET2
      Input packets : 0
      Output packets: 0
      Protocol inet, MTU: 1500
        Flags: None

    Logical interface fe-1/3/0.12 (Index 84) (SNMP ifIndex 23)
      Flags: SNMP-Traps 0x4000 VLAN-Tag [ 0x8100.100 ]    Encapsulation: ENET2
      Input packets : 0
      Output packets: 0
      Protocol inet, MTU: 1500

lab@M7i_GZ>
```

show　　show interface　　interface

```
lab@M7i_GZ# show interfaces
fe-1/3/0 {
    accounting-profile test;
    vlan-tagging;
    unit 0 {
        vlan-id 33;
        family inet;
    }
    unit 200 {
        vlan-id 200;
        family inet {
            address 202.103.224.1/24;
        }
    }
}

[edit]
lab@M7i_GZ#
```

show
run

```
lab@M7i_GZ# run show interfaces

Physical interface: fe-1/3/0, Enabled, Physical link is Up
  Interface index: 142, SNMP ifIndex: 31
```

Link-level type: Ethernet, MTU: 1518, Speed: 100mbps, Loopback: Disabled, Source filtering: Disabled,

Flow control: Enabled

Device flags : Present Running

Interface flags: SNMP-Traps Internal: 0x4000

CoS queues : 4 supported, 4 maximum usable queues

Current address: 00:05:85:dc:cc:db, Hardware address: 00:05:85:dc:cc:db

Last flapped : 2007-06-29 20:37:17 HKT (1w2d 00:36 ago)

Input rate : 792 bps (0 pps)

Output rate : 672 bps (0 pps)

Active alarms : None

Active defects : None

Logical interface fe-1/3/0.0 (Index 83) (SNMP ifIndex 71)

Flags: SNMP-Traps 0x4000 VLAN-Tag [0x8100.33] Encapsulation: ENET2

Input packets : 0

Output packets: 0

Protocol inet, MTU: 1500

Flags: None

[edit]

lab@M7i_GZ#

lab@M7i_GZ# **run ping 172.27.69.8**

PING 172.27.69.8 (172.27.69.8): 56 data bytes

64 bytes from 172.27.69.8: icmp_seq=0 ttl=64 time=5.118 ms

64 bytes from 172.27.69.8: icmp_seq=1 ttl=64 time=7.949 ms

64 bytes from 172.27.69.8: icmp_seq=2 ttl=64 time=7.018 ms

^C

--- 172.27.69.8 ping statistics ---

3 packets transmitted, 3 packets received, 0% packet loss

round-trip min/avg/max/stddev = 5.118/6.695/7.949/1.178 ms

[edit]

lab@M7i_GZ#

lab@M7i_GZ# **run ping 172.27.69.8** lab@M7i_GZ> **ping 172.27.69.8**

1.5. set

show show configure “

” show

display set set

```
lab@M7i_GZ# show protocols ospf
export Test_Policy_1;
area 0.0.0.0 {
    interface fe-1/3/0.0 {
        hello-interval 10;
    }
}

[edit]

lab@M7i_GZ# show protocols ospf | display set
set protocols ospf export Test_Policy_1
set protocols ospf area 0.0.0.0 interface fe-1/3/0.0 hello-interval 10

[edit]
lab@M7i_GZ#
```

1.6. commit rollback

cisco f ضخ



commit commit check

RE commit synchronize

rollback rollback 1
rollback 2 2

```
lab@M7i_GZ# show system host-name
host-name M7i_GZ;

[edit]
lab@M7i_GZ# set system host-name R1

[edit]
lab@M7i_GZ# commit
commit complete

[edit]
lab@R1# show system host-name
host-name R1;

[edit]
lab@R1# rollback 1
load complete

[edit]
lab@R1# show system host-name
host-name M7i_GZ;
```

[edit]
lab@R1# commit
commit complete

[edit]
lab@M7i_GZ#

2.

set system services ftp

ftp ftp ftp

set system name-server 192.168.1.1

2.2. SNMP

set snmp community <community> authorization < read-only/ read-write> clients <prefix> # SNMP

2.3.

IP Cisco RSR
unit vlan

set interface so-slot/pic/port interface

```
unit 0 {
    family inet {
        address 59.43.17.1/30;
    }
    family iso;
    family inet6 {
        address 2001:C68:100::3b2b:1101/126;
    }
    family mpls;
}
}
```

set chassis aggregated-devices ethernet device-count <count> #

```
        }
    }
```

2.4. VLAN

vlan

```
#                    100
set                          unit 0 family inet address 10.1.1.1/24 vrrp-group 0 preempt hold-time 30
#                           30
set                          unit 0 family inet address 10.1.1.1/24 vrrp-group 0 accept-data
```

```
                :
                    {
        vlan-tagging;
        unit 0 {
            vlan-id 10;
            family inet {
                address 10.1.1.1/24{
                    vrrp-
```

2.6.

set routing-options static route *network/mask* next-hop *address*
#

2.7. Policy

user@host# set policy-options policy-statement *policy-name* [term *name*] from *<conditions>*

```
lab@M7i_GZ#
Possible completions:
  area                 OSPF area identifier
+ as-path              Name of AS path regular expression (BGP only)
+ as-path-group        Name of AS path group (BGP only)
  color                Color (preference) value
+ community            BGP community
> external             External route
+ interface            Interface name or address
  level                IS-IS level
  local-preference     Local preference associated with a route
  metric               Metric value
+ neighbor             Neighboring router
+ next-hop             Next-hop router
  origin               BGP origin attribute
+ policy               Name of policy to evaluate
  preference           Preference value
> prefix-list          List of prefix-lists of routes to match
+ protocol             Protocol from which route was learned
> route-filter         List of routes to match
  route-type           Route type
> source-address-filter    List of source addresses to match
+ tag                  Tag string
{master}[edit]
lab@M7i_GZ#
```

policy From From

user@host# set policy-options policy-statement *policy-name* [term *name*] then *<action>*

```
lab@M7i_GZ#
Possible completions:
```

```
  accept                Accept a route
+ apply-groups          Groups from which to inherit configuration data
+ apply-groups-except   Don't inherit configuration data from these groups
> as-path-expand        Prepend AS numbers prior to adding local-as (BGP only)
  as-path-prepend       Prepend AS numbers to an AS path (BGP only)
  class                 Set class-of-service parameters
> color                 Color (preference) value
> community             BGP community properties associated with a route
  cos-next-hop-map      Set CoS-based next-hop map in forwarding table
  damping               Define BGP route flap damping parameters
  default-action        Set default policy action
  destination-class     Set destination class in forwarding table
> external              External route
  forwarding-class
```

```
lab@M7i_GZ#


{master}[edit]
lab@M7i_GZ#


{master}[edit]
lab@M7i_GZ#

{master}[edit]
lab@M7i_GZ#


{master}[edit]
lab@M7i_GZ#


{master}[edit]
lab@M7i_GZ#

{master}[edit]
lab@M7i_GZ#
policy-statement static-to-isis {
    from {
        protocol static;
        route-filter 219.142.80.63/32 exact;
        route-filter 202.97.3.0/24 exact;
    }
    then accept;
}
policy-statement load-balance {
    then {
        load-balance per-packet;
    }
}
policy-statement ldp-filter {
    term a {
        from {
            route-filter 59.43.8.0/21 prefix-length-range /30-/32;
        }
        then accept;
    }
}
```

```
{master}[edit]
lab@M7i_GZ#
```

2.8. GRE Tunnel

user@host#

2.9. NAT

IP 192.200.8.139 202.192.12.245 IP

output

```
set services nat rule nat-output match-direction output
set services nat rule nat-output term a from source-address 192.200.8.139/32
set services nat rule nat-output term a then translated source-prefix 202.192.12.245/32
set services nat rule nat-output term a then translated translation-type source static
```

input

```
set services nat rule nat-input match-direction input
```

3.

3.1.

RSR

1. console CIP CONSOLE
2. CLI
3.

```
user@host>
…
The operating system has halted.
Please press any key to reboot
```

4. console
5.

Juniper TAC JTAC

3.2.

RSR

1. console CIP CONSOLE
2. CLI
3.

```
user@host>
```

4. console
5.

“ ”

60

800

3.3. JUNOS

RSR JUNOS

1. console

7.

```
user@host>
Reboot the system ? [yes,no] (no)
```

```
< Press any key other than return >
ok      –
```

4. **recovery**

```
Enter full pathname of shell or 'recovery' for root password
```

800

3.5.

- _____
- _____
- _____
- _____

- CLI _____
- LED
- _____
- _____ JTAC _____

CLI

JUNOS CLI
CLI ping traceroute

Craft Interface CONSOLE ETHERNET AUXILIARY CLI

CLI “ _____ ”

LED

LED

- Craft Interface LED
- LED

Craft Interface LED

Craft Interface Craft Interface
LED LED Cutoff

LED

LED

- PIC LED——PIC LED
- LED—— OUTPUT OK LED

“ LED ”

Craft Interface LED
Craft Interface `show chassis alarms`

```
uer@host>
```

- Chassis alarms ——
- Interface alarms ——

“ LCD ” LCD “ CLI ”
`show chassis alarms`

3-1

FEB PIC

- FEB
- PIC

FEB

FEB FEB

FEB

- FEB
- Craft Interface LED FEB

PIC

PIC

- PIC LED
- CLI PIC

```
user@host>

Slot 0 Online
  PIC 0   4x OC-3 SONET, MM
  PIC 1   1x CSTM1, SMIR
  PIC 3   2x OC-3 ATM, MM
Slot 1 Online
  PIC 0   1x OC-12 SONET, MM
  PIC 1   1x OC-12 ATM, MM
  PIC 2   2x OC-3 ATM, MM
  PIC 3   2x OC-3 ATM, MM
```

OK LED FAULT

■ Craft Interface LED

```
user@host>
Class Item           Status  Measurement
...
Fans  Left Fan 1      OK     Spinning at normal speed
      Left Fan 2      OK     Spinning at normal speed
      Left Fan 3      OK     Spinning at normal speed
      Left Fan 4      OK     Spinning at normal speed
...
```

FEB

```
user@host>
Routing Engine status:
   Temperature        35 degrees C / 95 degrees F
   DRAM              768 MB
   Memory utilization   16 percent
   CPU utilization:
     User              0 percent
     Background         0 percent
     Kernel            0 percent
     Interrupt          0 percent
     Idle            100 percent
   Model                RE-2.0
   Serial ID             f1000004f91d2901
   Start time            2003-05-01 15:07:12 PDT
   Uptime               3 days, 9 hours, 4 minutes, 5 seconds
```

- FEB
- PIC

FEB

FEB FEB

- Console FEB
- FEB

```
user@host>

FEB status:
  Temperature           32 degrees C / 89 degrees F
  CPU utilization        3 percent
  Interrupt utilization   0 percent
  Heap utilization       18 percent
  Buffer utilization     44 percent
  Total CPU DRAM         64 MB
  Internet Processor I   Version 1, Foundry IBM, Part number 9
  Start time:             2003-05-01 15:08:59 PDT
  Uptime:                 3 days, 9 hours, 3 minutes, 13 seconds
```

PIC

PIC

- PIC LED PIC STATUS LED

  LED
-

```
user@host>

 Slot 0 Online
   PIC 0   4x OC-3 SONET, MM
   PIC 1   1x CSTM1, SMIR
   PIC 3   2x OC-3 ATM, MM
 Slot 1 Online
   PIC 0   1x OC-12 SONET, MM
   PIC 1   1x OC-12 ATM, MM
```

	FEB PIC



3-1

3-2

1. ESD Point
2.
3.



3-2

PFE

- FEB
- PIC
- SFP

FEB

FEB FEB 7 3.2 FEB

FEB

- FEB
- FEB



3-3 FEB

FPC

FEB 3-4 FEB

1. OFF(0)
2. ESD Point
3. FEB FEB
4. FEB FEB
5. FEB
6.
7. CLI show chassis feb FEB



3-4 FEB

PIC

PIC PIC PIC PIC

- PIC

■ PIC

PIC

PIC 3-5 PIC

1. PIC

2. ESD Point

3. PIC

■ PIC offline 5 FAIL LED

■

```
user@host>
```

4. PIC

5. PIC PIC

6. PIC

7. PIC

3-5 PIC

PIC

PIC 3-6 PIC

1. ESD Point

2. PIC PIC

3. PIC PIC PIC

4. PIC

- PIC offline 5 LED
-

```
user@host>
```



3-6 PIC

SFP

SFP Small form factor pluggable PIC 3-7 SFP



3-7 SFP

SFP SFP

SFP

- SFP
- SFP

SFP

SFP

1. SFP
2. ESD Point

3. SFP SFP

4. SFP

5.

6. SFP PIC SFP

SFP

PIC

1. ESD Point

2. SFP

3. PIC SFP SFP ś SFP

   ■ PIC 10 SFP ś SFP

   ■ PIC SFP ś FPC ś SFP

   FPC SFP

4. SFP PIC

5. SFP SFP

6.

7. PIC LED

ś

■ _____

■ _____

7 3.2

3-8

1.

2.

■ — -48V

7.

8.

9. |

LED OUTPUT OK LED



3-9



3-10

■ PC Card

■

PC Card

PC CARD Type I PCMACIA
PC Card JUNOS PC Card JUNOS
JUNOS PC Card

2. PC Card



3-13

RE

3-14

1. ESD Point
2.



3-15

- Ethernet
- Console Auxiliary

Ethernet

RJ45 ETHERNET Ethernet

1. ETHERNET

   3-16 Ethernet

2. ETHERNET RE0

   RE0 RE1 RE1

3.

3-16 Ethernet

Console Auxiliary

CIP CONSOLE Modem
CIP AUXILIARY RS-232

DB-9/DB-9

console auxiliary

1. CONSOLE AUXILIARY

- console auxiliary
-
-
-